

# AWZ540 V2.0 MZN1 Over voltage protection module



Edition: 4 from 20.02.2014 Supersedes: 3 from 28.06.2012

EN\*

#### 1. Description.

The over voltage protection module is intended for protecting systems powered with 12V DC against being supplied with too high supply power (e.g. as a result of damaged stabilising system of a PSU). When the maximum accessible input voltage is detected, the output is cut off protecting the receivers from damaging. Activation of the system is indicated by the red LED - L1.

#### 2. Module description.

## 2.1. Description of components and connectors of the module.

Element no. [fig. 1]	Description
[1]	L1 red LED (indicates activation of the system that cuts off the output voltage)
[2]	Screw connector – module's output
[3]	Screw connector – module's power input
[4]	Mounting panel

#### 3. Specifications.

Supply voltage	9 V÷ 40 V DC
Output voltage	9 V÷ 14,1 V DC (+/-0,4V)
Output disconnection	14,1V (+/-0,4V)
voltage	
Switching hysteresis	+/-0,1V
Load current	4A max
Voltage drop	ΔU=0,2V max @4A
Approximate time of voltage	100us @ I=1,7A
disconnection	
Approximate time of voltage	250us @ I=1,7A
connection	
LED indication	Red LED - L1- (indicates activation of the
LED Indication	system that cuts off the output voltage)
Operating conditions	II environmental class, -10℃ ÷ 50℃
Dimensions	50 x 26 x 43 (WxHxD)
Installation	linstallation tape or installation bolt x2
Connectors	Screw connectors Φ0,41÷1,63 (AWG 26-14)
Net/gross weight	0,02kg / 0,04kg
Declarations, warranty	CE, RoHS, 2 year from the production date




Fig.1. The view of the module.




Fig.2. Electrical scheme and voltage waveforms.

#### **WEEE PARKING**

According to the EU WEE Directive – It is required not to dispose of electric or electronic waste as unsorted municipal waste and to collect such WEEE separately.

#### WARRANTY

Pulsar K. Bogusz Sp.j. (the manufacturer) grants a two-year warranty for the equipment, counted from the device's production date.

### Pulsar K.Bogusz Sp.j.

Siedlec 150, 32-744 Łapczyca, Poland
Tel. (+48) 14-610-19-40, Fax. (+48) 14-610-19-50
e-mail: <a href="mailto:biuro@pulsar.pl">biuro@pulsar.pl</a>, <a href="mailto:sales@pulsar.pl">sales@pulsar.pl</a>
http://</a><a href="mailto:www.pulsar.pl">www.pulsar.pl</a>, <a href="mailto:www.pulsar.pl">www.zasilacze.pl</a>